



MS44

Features:

- Zinc die-cast housing, nickel-plated
- Excellent quality component, professional circuit design and low loss
- 13/18V、0/22KHz supplied by satellite receiver through coaxial cable to switch corresponding port
- Capable of connecting four SATV signals simultaneously
- Four SATV signals switched through 13/18V、0/22KHz
- Distributed into four subscribers to use simultaneously and no mutual interference
- Applicable to multi-satellite and multi-receiver usage
- Power supplied from satellite receiver or external power

MS-4401 Specifications :

Item	Specification	Item	Specification
Frequency Range	950-2150 (MHz)	Output Level	95(dBuV)
Insertion loss	5(dB)	Normal Working Voltage	12-20(V)
Isolation Between Outputs	25(dB)	DC Power Consumption	40(mA)
Switching Isolation Input	28(dB)	DC Max Power Passing	500(mA)
Return Loss Inputs	12(dB)	Supply Voltage	20V (±1) 700mA
Return Loss Outputs	8(dB)	Impedance(all ports)	75(Ω)

- Switching Voltage/Signal : 13/18V、0/22KHz
- Connectors:“F” type female

Leo Technology and Marketing Co.,Ltd.

56/32 Moo.1 Soi.Tha-It, RattanaTibeth Road. Tambon.Saima, Aumpur.Muean, Nonthaburi 11000
 Tel. +66-2926-1870-3, Fax. +66-2924-6644, Website. www.leotech.co.th